



Get the best from two antennas without the need for an additional switch. Whether you're in the high country, in rough terrain or on the flat, Oricom's Smart Dual Antenna Technology makes sure you stay in touch with all the features you'd expect from a heavy duty 5 watt UHF CB Radio.

# **KEY FEATURES**

- Integrated dual antenna system
- · Slimline transceiver
- 80 channels<sup>†</sup>
- 3 Memory Groups
- Heavy duty microphone
- Smart fast scanning (priority / group memory / group tone scanning)
- LCD 4 step brightness control
- Over voltage alert function
- 38 CTCSS and 104 DCS codes
- Multi-colour backlight with (96 different shades)
- Duplex (range extender)
- Rotary Volume, channel and squelch control
- 3.5mm external speaker jack
- Designed and engineered in Korea

# **UHF182 Technical Specification**

## **GENERAL**

Compliance	AS/NZS 4365:2011	
Frequency Range TX/RX	476.425 - 477.4125 MHz	
Number of TX/RX Channels	80 UHF CB	
Channel Spacing TX/RX	12.5KHz	
Operating modes	Simplex, Repeater TX offset (+750KHz)	
Scanning Speed	35 msec per channel	
Antenna Impedance	50 Ohms for ANT1, ANT2	
Operating Volts nominal	13.8VDC	
Operating Volts Range	10 to 15VDC	
Over Voltage Protection	Diode and Voltage regulator system	
Over Current Protection	2 AMP fuse	
Reverse Polarity Protection	Shunt diode	
Frequency stability	+/- 5 ppm	

#### **TRANSMITTER**

RF Output Power	Nominal 5 watts
Modulation	F3E(FM)
Maximum deviation	2.5KHz
Spurious Emissions	<-30dBm
TX Audio pre-emphasis	+6dB/Octave from 300Hz to 3KHz
Current consumption during TX	1.6AMP with 50ohm antenna termination

### **RECEIVER**

Circuit Type	Dual conversion super heterodyne	
Intermediate Frequencies	1'st IF : 21.4MHz , 2'nd IF : 450KHz	
Maximum useable sensitivity	-123dBm for 12dB SINAD un-weighted	
Audio output power	> 2 Watts at 8 ohm load	
RX Audio de-emphasis	+6dB/Octave from 300Hz to 3KHz	
Signal to Noise Ratio	>40dB	
Conducted Spurious Emission	>-57dBm	

#### **MECHANICAL**

Dimensions (H) X (W) X (D)	29 X 110 X 115	
Weight	425g with only main unit	

