# CONTROLLER SPEAKER MICROPHONE

5 WATT UHF CB RADIO





AUDIO EQUALISER



DUAL SPEAKER





## UHF360 CONTROLLER SPEAKER MICROPHONE



5 WATT UHF CB RADIO

The UHF360 removes the need for a head unit, with all of the radio's controls in the microphone. The integrated speaker in the controller mic works with the transceiver speaker to deliver exceptional sound quality and volume.

#### **KEY FEATURES**

- 5 watt (max TX power)
- Heavy duty controller speaker microphone
- Rugged micro size transceiver
- Large easy to read LCD display
- 38 CTCSS and 104 DCS codes
- Duplex (range extender)
- Open/Priority scan
- Priority channel
- 3.5mm external speaker jack
- Designed for Australian conditions. Made in Korea.



AUDIO EQUALISER



DUAL SPEAKER



RUGGED CONSTRUCTION



YEAR WARRANTY

### **UHF360 Technical Specification**

#### **GENERAL**

Frequency Range TX/RX	476.425 - 477.4125 MHz
Number of TX/RX Channels	80 UHF CB (75 Voice channels)
Channel Spacing TX/RX	12.5KHz
Operating modes	Simplex, Repeater TX offset (+750kHz)
Scanning Speed	130 msec per channel
Antenna Impedance	50 Ohms
Operating Volts nominal	13.8VDC
Operating Volts Range	10 to 15 VDC
Over Voltage Protection	voltage regulator
Over Current Protection	2 AMP fuse
Reverse Polarity Protection	Shunt diode
Frequency stability	+/- 2.5ppm

#### **TRANSMITTER**

RF Output Power	Nominal 5 watts
Modulation	F3E(FM)
Maximum deviation	2.5KHz
Spurious Emissions	< -70 dBc
TX Audio pre-emphasis	+ 6dB/octave from 300Hz to 3kHz
Current consumption during TX	1.5 Amps with 50 Ohm antenna termination

#### **RECEIVER**

Circuit Type	Direct conversion by Single DSP chip
Intermediate Frequencies	IF = 137KHz
Maximum useable sensitivity	Less than -122dBm at 12dB SINAD
Audio output power	3 Watts Maximum
RX Audio de-emphasis	-6dB/octave 300Hz to 3kHz

#### **MECHANICAL**

Transceiver Dimensions	27 (h) $\times$ 102 (w) $\times$ 85 (d) mm
------------------------	--

