

The wireless reversing camera with magnetic base offers convenient installation, a free app for viewing the camera feed, and enhanced visibility with infrared night vision producing a black and white image.







Oricom<sup>\*</sup> is the registered trade mark of Oricom Holdings Pty Ltd. All other trade marks are trade marks of their respective owners.



# WRC001 WIRELESS REVERSING CAMERA WITH MAGNETIC BASE







### **TECHNICAL SPECIFICATION**

| Battery Capacity           | 2160mAh                         |
|----------------------------|---------------------------------|
| Battery Voltage            | 3.7V Li-ion                     |
| Recharge Time              | Approx. 4.5 hours               |
| Max Recharge Current       | 480mA                           |
| Operating Current          | 260mA                           |
| Transmit Power             | 17.3dBm (53.5mW)                |
| Wireless Communication     | WiFi                            |
| Wireless Transfer Distance | Up to 15m (without obstruction) |
| Ingress Protection Rating  | IPX6                            |
|                            |                                 |

ORICOM

### **KEY FEATURES**

- View camera feed on FREE App
- Infrared night vision (black and white image)
- Colour daytime view
- Waterproof IPX6
- Up to 15m Range
- USB Charging
- Included Velcro for flexible mounting positions.

## PACK CONTENTS

- 1 x WRC001 Wireless reversing camera
- 1 x Magnetic base
- 1 x USB Charging cable (5V Power Adaptor not supplied)
- 1 x Velcro mounting tape\*

#### Velcro Tape Installation Instructions

UP TO 15M RANC

\*Velcro Tape: 3M™ Dual Lock™ Reclosable Fastener SJ3550. It is strongly recommended that the surface is thoroughly cleaned prior to application using IPA wipes, you can also use a primer to increase adhesion further. Installation temperature should be between 20-27°C, The pressure sensitive adhesive tape requires a clean dry surface and firm even pressure (15psi) to ensure good contact with the surface of the substrate to which it is being applied. It is advised to wait one hour after tape installation before installing the camera.



